

# **Of Household**

## HD IP Cameras V 2.1

More information can be downloaded at <u>www.cctvsno.com</u>

This manual applies to our household series IP cameras.

Please download the correct product CD information at <u>www.cctvsno.com</u> before operating the camera.

Recommended operating the IP camera according to the content below.

## Content

1.	About camera	3
2.	Connect camera	3
3.	View viamobile phone	6
4.	View via PC	7
5.	Set WIFI	9
6.	Set Micro SD card records	9
7.	Reboot and restore factory setting	11
8.	More info	12

# 1. About camera

#### **Product introduction.** 1.1

This is a digital HD IP camera for monitoring. It connects to the Internet to send and receive data, and you can use it to remotely view real-time images from your mobile phone, computer or other device anytime and anywhere, it can save surveillance videos in the Micro SD card, computer or other device such as an NVR, The camera also supports alarm functions such as sending alarm emails, alarming cell phone message push and other functions.

#### Product should contain: 1.2

IP Camera*1	Power adapter*1
User manual*1	Network cable*1
Bracket*1	Screws bag*1

#### 1.2 Interface.



## 2. Connect camera

2.1 Plug in power adapter and connect to camera, you can not connect the

network cable.



If you use a network cable to connect the camera to the router(The router must be able to connect to the Internet), you can jump directly to "3. View via mobile phone".

2.2 Camera will self test for one minute, then insistently give out the "ding-



If you don't hear "ding-ding-ding..."

sound, please reset the camera

until hear the sound.

2.3 Download "CamHi" from Google Play Store / Apple App Store or scan the

QR code below to get APP information.



### 2.4 Run APP and configure the WIFI of camera then follow the steps below.

●●●○○ 中国电信 🗢	13:20		●●●○○中国电信 令	13:20		**** 中国地区	e 1961		1
	Camera	Edit	<b>〈</b> Back	Add Camera	Done	< Back	Wireless Inc	3. enter WIFI	
<b>-</b>	Add Camera		Name	Camera	8	SSID	SNOCAM	password and click	
			User Name	admin	0	Password	23057712	"Set"	
(	1. click "Ad	Id	UID				Apply	$\sim$	
	camera"		Password	admin	8	Before click th	se Apply button, r	please turn the phone	
			🔡 Scan QF	R Code add UID	>	to the Do	Warnin you hear the sound	g If from camera?	
			Q Search o	camera from LAN	>		No	Yes	
			<ul> <li>Wireless</li> <li>United States</li> </ul>	a Installation A. click "WIFI Installation"	>		4. clic	k "YES"	
Camera F	Picture Video	About							

Make sure your phone is connected to WIFI and can connect to the internet. Your WIFI name must be english and can not contain special characters.

SSID	SNOCAM
Password	23057712
	Apply
Before click t volu to th	the Apply button, please turn the phone Wait for connecting
	Cancel
6	
	5. wait until camera
	WIFI connection
	completed



When the camera sends a "Dong — "tone, it means that the camera is connected to your WIFI, and the operation will jump to "3. View via mobile phone" step 3 of 3.1.

## 3. View via mobile phone

#### **3.1** Run APP then follow the steps below.

●●●○○ 中国电信 令	13:20		••••○ 中国电信 令	13:20		
	Camera	Edit	K Back	Add Camera	Done	And you can quickly enter
<b>-</b>	Add Camera		Name	Camera	0	the UID by scanning the
			User Name	admin	8	QR code on the camera's
1	1. click "Add		UID			label, as shown below
	camera"		Password	admin	0	
			🔡 Scan QF	Code add UID	>	
			Q Search o	camera from LAN	>	.= 102
				Λ		
			🛜 Wireless	Installation	>	
				Click here to		
				Search camera		
~		0				
Camera	Picture Video	About				A CONTRACT

Back Camera List Refresh Camera Add Camera	Done		Came	era	Edit
ievice on LAN:	Y				
))))))))))))))))))))))))))))))))))))))	8		Add Car	nera	
32.168.3.2 User Name admin	8		amera		6
UID DDD-042980-ZBZJW	8		DDD-042980-ZE	BZJW	50
3. click UID to Password admin	0				
Scan QR Code add UID	>	ca	5. click mera to	online monitor	
Q Search camera from LAN	>				)
Wireless Installation	>				
		<sup>™</sup>		8	(j)
		Camera	Picture	Video	About

## 4. View via PC

 $4.1 \quad Install the "Search tool" from the CD, then run it to find the cameras.$ 



4.2 Access to the camera through browser on windows PC.



if you do not use IE browser some settings will be missing.

### 4.3 Connect and manage the multiple cameras via CMS on windows PC!



CMSinstallationpackagesandinstructionsareavailableintheCD.

## 5. Set WIFI

## 5.1 Set WIFI on phone.

●●●●○中国电信 令	13:22		●●●●◎ 中国电信 令	13:22		••••• •• <b>E</b> ® <u>A</u> •••••	13:22	
	Camera	Edit	K Back	Camera Setting		K Back	Wi-Fi Setting	
	Add Camera			Camera DDDD-042980-ZBZJW		Current Wi-Fi SNOCAM		>
Or DD	nline DD-042980-ZBZJW	¢	Change Pass	sword	>		Wi-Fi manager	
C	1 aliak hara thar	5	Alarm Settin	g	>			
	into setting page	•	Action with A	Alarm	>	SNOCAM-office singal:100% W		>
			Audio Setting	a	>	TP-LINK_4E8 singal:89% Wi	ATKIN 3. select W	FI
			Video Settin	g	>	IPCAM-39117 singal:89% W	and ente password	r i
			Wi-Fi Setting		>	singal:89% W	IO	
			SD Card Set	ting 2. click"WI-F	- >	singal:83% W	PA_AES	
<del>گ</del> ا		(i)	Time Setting	Setting"	$\rightarrow$	IPCAM-39123 singal:83% W	13 PA_AES	2
Camera	Picture Video	About				IPCAM-39122	9	>
V	VIFInamem	ustbe	english a	and can not co	ontai	n special	characters.	
A	fter the WIFI	settin	g,ifthec	cameraisnot	conr	nected to	thenetwork	

cable, it will automatically switch to WIFI connection.

# 6. Set Micro SD card record

6.1 Set motion detection alarm recording on the phone.



## 6.2 Set schedule recording on phone.

••••• 中国电信 <b>〈</b> Back		edule	• <b></b>	中国电信 令 ck SD Ca	13:23 ard Setting
Recording	Length 600 st between 15 to 600	seconds	Tota Free	Il Size e size	7565
Enable Re	cord Schedule None Apply 1. oper Re	All Day	Form	Form at command will era 2. ch card	at SD Card se all date of SDCard neck the SD is available
			10 / <b>12</b>		

#### 6.3 Playback record on phone.



These parameters can be set in more detail via IE browser on the PC!

## 7. Reboot and restore factory settings

7.1 Reconnect the power to restart the camera.



7.2 Press and hold the reset button for 5 seconds and the camera will restore



Also you can restart or reset the camera via mobile phone or PC.

## 8. More info

This manual is to help customers to know and use the camera quickly, For detailed instructions and video tutorials please refer to the content of CD information at <u>www.cctvsno.com</u>.

This manual may have descriptions and operations that do not match the product, If you have any questions or need technical support Please feel free to contact us or our dealers.